



## INTRODUCTION

Aksa power generation system, providing optimum performance, and reliability, for stationary standby, prime power, and continuous duty applications. All generator sets are factory build, and production tested.

### Power (kVA)

3 Phase, 50 Hz, PF 0.8

Voltage	STANDBY RATING (ESP)		PRIME RATING (PRP)		Standby Amper
	kW	kVA	kW	kVA	
400/231	528,00	660,00	480,00	600,00	952,66

**STANDBY RATING (ESP)** Applicable for supplying power to varying electrical load for the duration of power interruption of a reliable utility source. ESP is in accordance with ISO 8528-1. Overload is not allowed.

**PRIME RATING (PRP)** Applicable for supplying power to varying electrical load for unlimited hours. PRP is in accordance with ISO 8528-1. 10 % overload capability is available for a period of 1 hour within 12-hour period of operation.

### General Characteristics

Model Name	AP 660
Frequency (Hz)	50
Fuel Type	Diesel
Engine Made and Model	PERKINS 2806A-E18TAG1A
Alternator Made and Model	ECO 40-2L/4 C
Control Panel Model	DSE 7320
Canopy	MS 86-AP660

### ENGINE SPECIFICATIONS

Engine	PERKINS
Engine Model	2806A-E18TAG1A
Number of Cylinder (L)	6 cylinders - in line
Bore (mm.)	145
Stroke (mm.)	183
Displacement (lt.)	18,13
Aspiration	Turbo Charged and Charge Air Cooled
Compression Ratio	14,5:1
RPM (d/dk)	1500
Oil Capacity (Total With Filter) (lt)	62
Standby Power (kW/HP)	593/795
Prime Power	540/724
Block Heater QTY	1
Block Heater Power (Watt)	3000
Fuel Type	Diesel
Type of Fuel Pump	MEUI
Governor System	ECM
Operating Voltage (Vdc)	24 Vdc
Battery and Capacity (Qty/Ah)	2x143



Charge Alternator (A)	45
Cooling Method	Water Cooled
Cooling Fan Air Flow (m3/min)	650
Coolant Capacity (engine only / with radiator) (lt)	/61
Air Filter	Dry Type
Fuel Cons. Prime With %100 Load (lt/hr)	123
Fuel Cons. Prime With %75 Load (lt/hr)	90
Fuel Cons. Prime With %50 Load (lt/hr)	61

### ALTERNATOR CHARACTERISTICS

Manufacturer	Mecc Alte
Alternator Made and Model	ECO 40-2L/4 C
Frequency (Hz)	50
Power (kVA)	625
Voltage (V)	400
Phase	3
A.V.R.	DER1
Voltage Regulation	(+/-)0.5%
Insulation System	H
Protection	IP23
Rated Power Factor	0.8
WEIGHT COMP. GENERATOR (Kg)	1456
COOLING AIR (m <sup>3</sup> /min)	54

### Open Gen.Set Dimensions (mm)

LENGTH	3450
WIDTH	1800
HEIGHT	2171
DRY WEIGHT (kg.)	4250
TANK CAPACITY (lt.)	1150

### Gen.Set Canopy Dimensions (mm)

LENGTH	5383
WIDTH	1800
HEIGHT	2503
DRY WEIGHT (kg.)	5670
TANK CAPACITY (lt.)	1150

### INTRODUCTION

No Data



### Control Panel

Control Module	DSE
Control Module Model	DSE 7320
Communication Ports	MODBUS
	<ol style="list-style-type: none"> <li>1. Menu navigation buttons</li> <li>2. Close mains button</li> <li>3. Main Status and instrumentation display</li> <li>4. Alarm LED's</li> <li>5. Close generator button</li> <li>6. Status LED's</li> <li>7. Operation selecting buttons</li> </ol>

### Devices

DSE, model 7320 Auto Mains Failure control module Static battery charger Emergency stop push button and fuses for control circuits

### CONSTRUCTION and FINISH

Comonents installed in sheet steel enclosure.

Phosphate chemical, pre-coating of steel provides corrosion resistant surface

Polyester composite powder topcoat forms high gloss and extremely durable finish

Lockable hinged panel door provides for easy component access

### INSTALLATION

Control panel is mounted generating set baseframe on robust steel stand or power module. Located at side of generating set with properly panel visibility.

### GENERATING SET CONTROL UNIT

The DSE 7320 conrol module is a standard addition to our generator sets from 220 kVA upwards and it has been designed to start and stop diesel andgas generating sets that include electronic and non electronic engines.

The DSE 7320 includes the additional capability of being able to monitor a mains (utility) supply and is therefore suitable for controlling a standby generating set in conjunction with an automatic transfer switch.

The DSE7320 also indicates operational status and fault conditions, automatically shutting down the generating set and indicating faults by means of its LCD display on the front panel.

### STANDARD SPECIFICATIONS

- Microprocessor controlled
- 132 x 64 pixel LCD display makes information easy to read
- Front panel programming and also via PC software
- Soft touch membrane keypad and five key menu navigation
- Remote communications via RS232, RS485 and ethernet.
- Event logging (50) showing date and time
- Multiple date and time engine exercise mode and maintenance scheduler
- Engine block heater control.
- Controls; stop, manuel, auto, test, start, mute lamb test/transfer to generator, transfer to mains, menu navigation.

### Instruments

#### ENGINE

Engine speed

Oil pressure

Coolant temperature



Run time Battery volts

Engine maintenance due

GENERATOR

Voltage (L-L, L-N)

Current (L1-L2-L3)

Frequency

Earth current

kW

Pf

kVAr

kWh, kVAh, kVArh

Phase sequence

MAINS

Voltage (L-L, L-N)

Frequency

WARNING

Charge failure

Battery under voltage

Fail to stop

Low fuel level (opt.)

kW over load

Negative phase sequence

Loss of speed signal

PRE-ALARMS

Low oil pressure

High engine temperature

Low engine temperature

Over /Under speed

Under/over generator frequency

Under/over generator voltage

ECU warning

SHUT DOWNS

Fail to start

Emergency stop

Low oil pressure

High engine temperature

Low coolant level

Over /Under speed



Under/over generator frequency  
Under/over generator voltage  
Oil pressure sensor open  
Phase rotation  
ELECTRICAL TRIP  
Earth fault  
kW over load  
Generator over current  
Negative phase sequence

**Options**

High oil temperature shut down  
Low fuel level shut down  
Low fuel level alarm  
High fuel level alarm  
EXPANSION MODULES  
Editional LED module (2548)  
Expansion relay module (2157)  
Expansion input module (2130)

**Standards**

Electrical Safety / EMC compatibility  
BS EN 60950 Electrical business equipment  
BS EN 61000-6-2 EMC immunity standard  
BS EN 61000-6-4 EMC emission standard

**STATIC BATTERY CHARGER**

Battery charger is manufactured with switching-mode and SMD technology and it has high efficiency.

Battery charger models' output V-I characteristic is very close to square

2405 has fully output short circuit protection and it can be used as a current source.

2405 charger has high efficiency, long life, low failure rate, light weight and low heat radiated in accordance with linear alternatives.

The charger is fitted with a protection diode across the output.

Charge fail output is available.

Connect charge fail relay coil between positive output and CF output.

Input: 196-264V.

Output: 27,6V 5A or 13,8V 5A.

**STANDARD SPECIFICATIONS**

- - Water cooled, Diesel engine
- - Radiator with mechanical fan
- - Protective grille for rotating and hot parts



- - Electric starter and charge alternator
- - Starting battery (with lead acid) including rack and cables
- - Engine coolant heater
- - Base frame design incorporates an integral fuel tank and anti-vibration isolators
- - Flexible fuel connection hoses
- - Single bearing, class H alternator
- - Industrial exhaust silencer and steel bellows supplied separately(for open sets)
- - Static battery charger
- - Manual for application and installation

## OPTIONAL EQUIPMENTS

### ENGINE

Fuel-Water Separator Filter

Oil heater

### ALTERNATOR

Anti-Condensation Heater

Over sized alternator

Main line circuit breaker

### CONTROL SYSTEM

Remote annunciator panel

Remote relay output

Alarm output relays

Remote communication with modem

Earth fault, single set

Charge Ammeter

### TRANSFER SWITCH

Three or four pole contactor

Three or four pole motor operated circuit breaker

### OTHER ACCESSORIES

Main Fuel Tank

Automatic or manual fuel filling system

Manual oil drain pump

Electrical oil drain pump

Residential silencer

Enclosure: weather protective or sound attenuated

Duct adapter ( on radiator)

Inlet and outlet motorised louvers

Inlet and outlet acoustic baffles

Trailer

Tool kit for maintenance

Supplied with oil and coolant - 30 °C



Battery isolating switch

#### **AKSA CERTIFICATES**

- TS ISO 8528
- CE
- SZUTEST
- 2000/14/EC